

MXA60

INTEGRATED AUDIO SYSTEM

McIntosh

The Compendium



FRONT PANEL: LED/fiber-optic illuminated green nomenclature. Left illuminated OUTPUT POWER meter (linear WATTS). Tube can be seen through the clear rectangle between the meters. Right illuminated OUTPUT POWER meter (linear WATTS). ⚡ Concentric TUNE / INPUT control. Digital information display. VOLUME control. ⚡ Touch button: STORE / CLEAR. Power indicator. HEADPHONES jack. ⚡ Touch buttons: ⏪ BACK, NEXT ⏩, TIME. Digital information display. Touch buttons: SACD/CD, ▶ PLAY/ II PAUSE, STOP/OPEN.



BACK PANEL: Gold plated RIGHT channel OUTPUT terminals for 8 Ω speakers. Gold plated LEFT channel OUTPUT terminals for 8 Ω speakers. ⚡ Inputs: RAA2 AM ANTENNA, coaxial FM ANTENNA, balanced LINE 2: Right & Left, unbalanced LINE 1: Right & Left. OUTPUTS: MAIN / SUB, 2 POWER CONTROL. Power cord receptacle.

MXA60

INTEGRATED AUDIO SYSTEM

McIntosh

The Compendium

AMP/PREAMP SPECIFICATIONS: **Frequency Response:** 20-20kHz (+0,-0.5dB), 20-100kHz (+0,-3dB). **Distortion:** 0.05%. **Signal to Noise Ratio:** 98dBA. **Input Sensitivity and Impedance:** 20K ohms. Input 1: 300mV unbalanced and Input 2: 600mV balanced. **Output Impedance:** main and sub 1.2V at 500 ohms. **Headphone Impedance:** 20 to 300 ohms. **Wide Band Damping Factor:** greater than 100. **Dynamic Headroom:** 1.6dB. **Power Requirements:** 120V at 25 watts. Has hand remote **HR60**.

FM TUNER SPECIFICATIONS: **Tuning Range:** 87.5 ~ 108Mhz (Europe); 87.9 ~ 107.9Mhz (USA); 76 ~ 90Mhz (Japan). **Frequency Response:** 20-15kHz \pm 1dB. **Harmonic Distortion:** 0.4% Mono; 0.8% Stereo, 20-100kHz (+0,-3dB). **Signal to Noise Ratio:** 70dB Mono; 68 dB Stereo. **Useable Sensitivity:** 2.2uV (18.1dBf). **50dB Quieting Sensitivity:** 1.5uV (14.8dBf). **Channel Selectivity:** 60dB adjacent channel; 66dB alternate channel. **Stereo Separation:** 38dB.

AM TUNER SPECIFICATIONS: **Tuning Range:** 522 ~ 1602khz (Europe); 530 ~ 710khz (USA); 522 ~ 1611khz (Japan). **Frequency Response:** 50 ~ 3,000Hz (+0,-6dB). **Harmonic Distortion:** .5%. **Signal to Noise Ratio:** 50dB. **Sensitivity:** 350uV/m. **Selectivity:** 45dB adjacent channel.



MXA60 - Sold from 2011 - 2016. S/N: ZR1011~ZR????

Size: 10-7/8"H, 22"W and 16"D. **Weight:** 64 lb. **\$7,500.00**