

MA 2275

STEREO INTEGRATED AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with LED/fiber-optic illuminated green/gold nomenclature. Left and right **POWER OUTPUT** meters (**LINEAR WATTS** or **DECIBELS**). ⚡ **INPUT SELECTOR** with indicator lights: **PHONO**, **CD 2**, **CD**, **TUNER**, **DVD**, **TAPE**. **BASS**. **TREBLE**. **METER CONTROL**: **LIGHTS OFF**, **WATTS** or **HOLD**. **BALANCE**. **VOLUME**. ⚡ **HEADPHONES** jack. **IR** sensor. Pushbutton switches: **RECORD MONITOR** (with indicator), **TONE BYPASS**, **MONO**, **MUTE**, **STANDBY/ON** (with indicator). **TUBE WARMUP** indicator. **POWER**: **ON** or **OFF**.



BACK PANEL: Polished stainless steel chassis. **RIGHT** channel **OUTPUT** binding posts for 2 Ω , 4 Ω or 8 Ω speakers. **LEFT** channel **OUTPUT** binding posts for 2 Ω , 4 Ω or 8 Ω speakers. ⚡ Jumper: **POWER AMP INPUT**, **PREAMP OUTPUTS 1**. **PREAMP OUTPUTS 2**. **TAPE OUTPUTS**. **INPUTS**: **TAPE**, **DVD**, **TUNER**, **CD**, **CD 2**, and **PHONO**. **GROUND** binding post. ⚡ **Power cord** receptacle. **FUSE**. **Coax EXTERNAL SENSOR** connector. **POWER CONTROL** output: **MAIN** and **Accessory**. **DATA PORTS**: **SUM**, **TAPE**, **DVD**, **TUNER**, **CD 2**, **CD**, and **PHONO**. **Balanced CD INPUT**.

MA 2275

STEREO INTEGRATED AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: 75w/ch into 2 ohms, 4 or 8 ohms. **Response:** 20-20kHz (+0 - 0.5dB). **Distortion:** 0.5%. **Noise and Hum:** 100dB power amp, -93dB high level, -80dB low level re 10mV. **Damping Factor:** greater than 18. **Input Sensitivity and Impedance:** high level 0.25V (8V max) at 22k, phono 2.5mV (90mV max) at 47k and 65pF. **Unity coupled.** **Power Requirements:** 120V at 3 Amps. Has hand remote **HR044** and **HR093** replacement.

TUBES: 4-**KT88/6550** output, 4-**12AX7A**, 2-**12AT7**. Solid state rectifier bridges.



MA 2275 - Sold from 2004 - 2011. S/N: XB1001~XB???? and VK1001~VK????

Size: 10-1/8"H, 17-3/4"W and 18-3/4"D. **Weight:** 77 lbs. **\$6,100.00**