

# C 2200

STEREO PRE-AMPLIFIER /  
VIDEO CONTROL CENTER

McIntosh  
The Compendium



**FRONT PANEL:** Glass with illuminated teal/gold nomenclature. **INPUT.** Illuminated left and right **OUTPUT LEVEL** meters (DECIBELS). **VOLUME.** ⚡ **BASS.** **TREBLE.** Digital display. **METER LIGHTS:** ON or OFF / **SETUP.** **BALANCE:** L to R. ⚡ **IR SENSOR.** Touch buttons: **TONE BYPASS**, **MONO**, **REC MONITOR**, **SETUP.** **HEADPHONES** jack. Touch buttons: **MUTE**, (with indicators): **OUTPUTS 1**, **OUTPUTS 2**, **STANDBY/ON.** **POWER** switch: ON or OFF.



**BACK PANEL:** Left and Right balanced **OUTPUTS:** MAIN, 2, and 1. Left and Right balanced **INPUTS:** VCR, SAT, DVD and CD. **GROUND** binding post. ⚡ Left and Right unbalanced **OUTPUTS:** MAIN, 2, 1 and TAPE/REC. Unbalanced **INPUTS:** TAPE/REC, VCR, SAT, DVD, CD, CD 2, TUNER and PH/AUX. ⚡ **Power** cord receptacle. **FUSE.** **POWER CONTROL** outputs: MAIN, ACC, 2 and 1. **PASS THRU** power control. **Coax** **EXTERNAL SENSOR** connector. **DATA PORTS:** TAPE, VCR, SAT, DVD, CD, CD 2, TUNER.

**SPECIFICATIONS:** **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.08%. **Noise and Hum:** - 93dB high level, -80dB phono. **Maximum Output:** 8V unbalanced, 16V balanced. **Output Impedance:** 500 ohms balanced and 250 ohms unbalanced. **Input Sensitivity and Impedance:** high level 0.45V (2.5V max) at 22k unbalanced and 44k balanced, phono MM 4.4mV (50mV max) at 47k and 65pF. **Power Requirements:** 120V at 75 Watts. Has hand remote **HR044** and **HR093** replacement.

**TUBES:** 4-12AX7A, 4-12AT7A. Solid state rectifier bridges.

# C 2200

STEREO PRE-AMPLIFIER /  
VIDEO CONTROL CENTER

McIntosh  
The Compendium



Also available as the **C 2000G** and **C 2000FG**.

**C 2200** - Sold from 2001 - 2009. S/N: TS1001~TS????, TU1001~TU???? and  
XG1001~XG????

**Size:** 7-5/8"H, 17-1/2"W and 20"D behind panel. **Weight:** 26-3/4 lb. **\$4,600.00**