

MR 55A

AM-FM MONAURAL TUNER

McIntosh
The Compendium



FRONT PANEL: Anodized gold and black aluminum panel. Illuminated dial. FM light. AM light. Signal strength indicator: 0 to 5. Tuning indicator: - to +. MC light. KC light. Tuning control. ⚡ FM AFC control: MIN to MAX or OFF. AM SENSITIVITY switch: greatest, intermediate or minimum. VOLUME control with on-OFF switch. SELECTOR switch: FM LISTEN, FM TUNE, AM BROAD, AM MEDIUM, AM SHARP or PHONO.



BACK PANEL: Screw terminals for FM ANTENNA and TO TV SET. GROUND screw. Power cord. FUSE. Unswitched AC outlet. PANEL LAMPS switch: HIGH or LOW. AM ANTENNA switch: ANTENNA or LOOP. Screw terminals for AM ANTENNA connections: HI, LO and GND. 2 audio OUTPUTS. MULTIPLEX OUTPUT. PHONO INPUT.

FM SECTION: **Sensitivity:** 3uV. **Response:** 20-20kHz within 3dB. **Distortion:** less than 3%. **Capture Ratio:** 1 to 0.8. Four IF stages. Two limiters.

AM SECTION: **Sensitivity:** 1.5uV. **Selectivity Bandwidth:** 20-9kHz, 20-6.5kHz, and 20-2kHz. **Whistle Filter:** 70dB reject at 10kHz.

TUBES: 6BK7, 2-6AB4, 2-6BA6, 4-6AU6, 6AL5, 2-6BN8, 6U8, 12AU7, 6BE6, 6BW4.

Power Requirements: 120V at 75 Watts.

CABINET: L 66

MR 55A

AM-FM MONAURAL TUNER

McIntosh

The Compendium



MR 55A - Sold from June 1959 - August 1962. S/N: 3K001~4K697 (1,696 UNITS)

Size: 4-3/4"H, 14-3/4"W and 12"D. **Weight:** 17 lbs-3 oz. **\$276.00**