

# MR 73

## AM - FM STEREO TUNER

# McIntosh

## The Compendium



**FRONT PANEL:** Glass with illuminated teal/gold nomenclature. Illuminated tuning dial. STEREO MPX indicator. Electron ray tube MULTIPATH indicator. Illuminated SIGNAL STRENGTH meter. Illuminated FM TUNING meter. Tuning control. ⚡ MODE SELECTOR switch: AM, FM or FM MONO. STEREO FILTER switch: OUT or IN. FM MUTING switch: OUT or IN. VOLUME with on-OFF switch. PANLOC buttons.



**BACK PANEL:** TP1 and TP2 scope outputs. Switched AC outlet. FUSE. Power cord. AM ANTENNA switch: EXTERNAL or LOOP. Built-in AM ferrite loopstick. Push terminals for external AM ANTENNA, GND and 300 Ω FM ANTENNA. 75 Ω FM ANTENNA coax input. LEFT & RIGHT AUDIO OUTPUTS: 2.5V FIXED OUTPUT and FRONT PANEL CONTROLLED. Panloc mounting.



**TOP PANEL:** MUTING: ON or OFF. AM SENSITIVITY: LOW or HIGH. DIAL SCALE INTENSITY: DIM or BRIGHT.

**AM SECTION:** *Sensitivity:* 12uV. *Response:* -6dB at 5kHz. *Distortion:* 1.0%. *Adjacent Channel Selectivity:* 30dB. *S/N:* 55dB. *Image Rejection:* 60dB.

# MR 73

## AM - FM STEREO TUNER

# McIntosh

## The Compendium

**FM SECTION:** *Sensitivity:* 2.5uV. *Response:* 20-20kHz (+1 -1dB). *Distortion:* 0.7% in stereo. *Capture Ratio:* 1.5dB. *Image Rejection:* 70dB. *S/N:* 70dB. *Separation:* 35dB@1kHz. *Spurious Rejection:* 90dB. *SCA Rejection:* 50dB.  
**Power Requirements:** 105~125V at 20 Watts.

**CABINET:** L 12 Also fits L 11, L 52, and L 62

**PANLOC BRACKETS:** Right - 043-592 / Left - 043-593



**MR 73** - Sold from June 1969 - December 1971. S/N: 10T01~37T75 (2,773 UNITS)

**Size:** 5-7/16"H, 16"W and 13"D behind panel. **Weight:** 24 lb. **\$549.00**