

MR 75

AM - FM STEREO TUNER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. FM MPX light. LED column for SIGNAL STRENGTH. TUNING indicator: - to +. Illuminated tuning dial. AM, FM and MUTE indicator lights. Tuning control. ⚡ SELECTOR switch: AM or FM. MODE switch: STEREO or MONO. HEADPHONES jack. MUTE switch: OFF or ON. VOLUME with on-OFF switch. PANLOC buttons.



REAR PANEL: Push terminals for external AM ANTENNA, GND, 300 Ω FM. 75 Ω FM ANTenna coax input. FM PRESELECTION switch: IN or OUT. Built-in ferrite AM loopstick. ⚡ Power cord. UNSWITCHED AC outlet. FUSE. SCOPE outputs: VERT (TP1) and HORIZ (TP2). Audio OUTPUTS: Left & Right 2.5V VARIABLE and 1V FIXED. Panloc mounting.

FM SECTION: **Sensitivity:** 11.2dBf or 2uV. **Stereo 50dB Quieting Sensitivity:** 39dBf or 50uV. **Response:** 20-15kHz (+0 -1dB). **Distortion:** 0.38% in stereo. **Capture Ratio:** 1.8dB. **Image Rejection:** 100dB. **S/N:** 70dB. **Alternate Channel Selectivity:** 75dB. **Separation:** 45dB@1kHz. **Spurious Rejection:** 100dB. **SCA Rejection:** 60dB.

AM SECTION: **Sensitivity:** 75uV. **Response:** 20-3.5kHz (+0 -6dB). **Distortion:** 0.8%. **Adjacent Channel Selectivity:** 30dB. **S/N:** 45dB. **Image Rejection:** 65dB. **Power Requirements:** 120V at 20 Watts.

CABINET: L 52 Also fits L 11, L 12, and L 62

PANLOC BRACKETS: Right - 0??-??? / Left - 0??-???

MR 75

AM - FM STEREO TUNER

McIntosh
The Compendium



MR 75 - Sold from July 1980 - September 1985. S/N: CR1001~CR1999 (998 UNITS)
Size: 5-7/16"H, 16"W and 13"D behind panel. **Weight:** 23 lb. **\$1,349.00**