

MR 85

AM - FM STEREO TUNER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. PRESET control. Digital readout: preset station tuned, frequency display, broadcast band and signal strength. FM stereo signal light. TUNING control. ⚡ Push buttons: ENTER (with indicator), DISPLAY, SPATIAL (with indicator), MONO, TUNER 1 or 2, AM or FM, ▼ SEEK, SEEK ▲, AUTOMUTE (with indicator), STANDBY/ON (with indicator), POWER ON or OFF. Additional AM/FM **TM 1** tuner is optional.



BACK PANEL: ANTENNA 1: external AM ANTenna (**RAA1**) and 75 Ω FM ANTenna coax input. TUNER 1 OUTPUT LEVEL control. Left & Right TUNER 1 VARIABLE and FIXED OUTPUTS. POWER CONTROL IN and OUT. Power cord receptacle. DATA IN jacks for TUNER 1 and 2. Left & Right TUNER 2 VARIABLE and FIXED OUTPUTS. TUNER 2 OUTPUT LEVEL control. Spaces reserved for optional **TM 1** second tuner module: ANTENNA 2: external AM ANTenna (**RAA1**) and 75 Ω FM ANTenna coax input.

FM SECTION: Sensitivity: 14dB μ F or 1.4 μ V across 75 ohms. **Stereo 50dB Quieting Sensitivity:** 35dB μ F or 15 μ V across 75 ohms. **Response:** 20-15kHz (+0 -1dB). **Distortion:** 0.45% in stereo. **Capture Ratio:** 1.2dB. **Image Rejection:** 75dB. S/N: 70dB stereo. **Alternate Channel Selectivity:** 75dB. **Separation:** 45dB. **Spurious Rejection:** 100dB.

AM SECTION: Sensitivity: 20 μ V. **Response:** 50-6kHz NRSC. **Distortion:** 0.5%. **Adjacent Channel Selectivity:** 45dB. **S/N:** 58dB. **Image Rejection:** 65dB. **Power Requirements:** 120V at 20 Watts.

OTHER: Optional **TM 1** second tuner can be mounted inside of chassis.

MR 85

AM - FM STEREO TUNER

McIntosh
The Compendium



MR 85 - Sold from 2000 - 2010. S/N: SE1001~SE????

Size: 5.44"H, 17.5"W and 17.5"D behind panel. **Weight:** 25.5 lb. **\$1,950.00**