

MR 88

AM/FM/XM/HD TUNER

McIntosh

The Compendium



FRONT PANEL: Glass with LED/fiber-optic illuminated green/gold nomenclature. IR remote sensor. PRESET / MENU control. Dial glass with electronic tuning pointer. Indicators for AM, FM, XM, HD, STEREO reception. TUNE / ADJUST control. ⚡ Touch buttons: CATEGORY (with indicator), DISPLAY, MONO / SETUP (with indicator), STORE / EXIT (with indicator). Digital information display. Touch buttons: ▼ SEEK ▲ / ▼ CATEGORY ▲, BAND, STANDBY/ON / RESET (with indicator).



BACK PANEL: RS-232C connector. SERVICE PORT. POWER CONTROL Input / Output. DATA Input / IR Input. XM input. 75 Ω FM ANTENNA coax input. RAA2 AM ANTENNA input. ⚡ Power cord receptacle. OUTPUTS: DIGITAL OPTICAL and COAXIAL. UNBALANCED Left & Right. BALANCED Right & Left.

FM HD SECTION: **Sensitivity:** -85dBm. **Response:** 20-20kHz. **Harmonic Distortion:** 0.1%. **Signal to Noise Ratio:** 85dB. **Stereo Separation:** 80dB.

FM SECTION: **Sensitivity:** 15.2dBf or 1.6uV across 75 ohms. **Stereo 50dB Quieting Sensitivity:** 16.2dBf or 1.85uV across 75 ohms. **Response:** 20-15kHz. **Distortion:** 0.1% in mono, 0.4% in stereo. **S/N Ratio:** 75dB in mono, 72dB in stereo. **Alternate Channel Selectivity:** 74dB. **Adjacent Channel Selectivity:** 65dB. **Stereo Separation:** 35dB.

AM HD SECTION: **Response:** 20-15kHz. **Harmonic Distortion:** 0.1%. **Stereo Separation:** 75dB. **Signal to Noise Ratio:** 85dB.

MR 88

AM/FM/XM/HD TUNER

McIntosh

The Compendium

AM SECTION: *Sensitivity:* 550uV/m. *Response:* 100-3,500 Hz. *Distortion:* 0.25% at 80% modulation. *Adjacent Channel Selectivity:* 50dB. *S/N Ratio:* 45dB.

GENERAL SPECIFICATIONS: *FM tuning Range and Channel Spacing:* 87.5Mhz ~ 107.9 Mhz; 200kHz. *FM Antenna Input:* 75 ohms, type "F" coax connector. **AM Tuning Range and Channel Spacing:** 530kHz ~ 1710kHz; 10kHz. **Rated Output:** 1 Vms Unbalanced, 2 Vms Balanced. **Output Impedance:** 100 ohms Unbalanced or Balanced. **Digital Output Optical:** -15dbm to -21dbm (PCM), Coaxial: 0.5V p-p/75 ohm (PCM). **AM Antenna Input:** Balanced, RJ45 connector (for use only with supplied **McIntosh RAA2** remote AM antenna).

Power Requirements: 120V at 30 Watts. Has hand remote **HR070**.



MR 88 - Sold from 2011 - 2018. S/N: ZK1001~ZK????

Size: 6"H, 17.5"W and 18"D behind panel. **Weight:** 25.5 lb. **\$4,500.00**