

MPI 4

MAXIMUM PERFORMANCE INDICATOR / FM MULTIPATH TUNING INDICATOR

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. Calibrated reticle screen. POWER LED column in 10dB steps from 0.1W to 1000W. PREAMP LED indicator. SWEEP. HORIZONTAL. VERTICAL. INTENSITY. POWER LEVEL. GAIN with on/OFF switch. 7 Pushbutton switches: SWEEP FREQUENCY: 20-200, 200-2K, 2K-20K. MODE SELECTOR: L, (DUAL TRACE), R, LEVEL, STEREO, MULTIPATH. INPUT AUDIO jack. PANLOC buttons.



BACK PANEL: Power cord. FUSE. Unswitched AC outlet. POWER AMP: Push terminals for: LEFT and RIGHT speaker inputs. SPEAKER IMPEDANCE switch: 4 Ω, 8 Ω or 16 Ω. PREAMP: LEFT AUDIO INPUT, LEFT AUDIO OUTPUT, RIGHT AUDIO INPUT, RIGHT AUDIO OUTPUT. TUNER: SIGNAL STRENGTH (TP 1), DEVIATION (TP 2). Panloc mounting.



TOP PANEL: LEVEL MODE: NORMAL, PEAK, RESET. RETICLE ILLUMINATION: OFF or ON. LOW PASS FILTER: OUT or IN. FOCUS. SWEEP: TRIGGER SOURCE: LEFT, RIGHT, LINE, TRACE SEPARATION: MIN to MAX, SWEEP EXPANSION: 0.25 to 5. TUNER: MULTIPATH POLARITY + or -, SIGNAL STRENGTH, DEVIATION. AUDIO TRIM: LEFT and RIGHT.

CABINET: L 12 Also fits L 11, L 52, and L 62

MPI 4

MAXIMUM PERFORMANCE INDICATOR / FM MULTIPATH TUNING INDICATOR

McIntosh

The Compendium

SPECIFICATIONS: *Multipath Mode:* sensitivity: 100mV/cm; response dc to 50kHz (-3dB); input impedance: 250k; signal strength polarity positive or negative. *Stereo Mode:* sensitivity (vertical and horizontal) 1.75mV rms/cm (5mV p-p/cm); response: 5Hz to 50kHz (-3dB); input impedance 250k. *Power Level Mode:* sensitivity: 0.1 to 1000 average watts for full scale indication (+3dB) in 9 calibrated steps; response: 5Hz to 100kHz (-3dB); input impedance: 75k, sensitivity 0.1 to 1000 average watts for full scale indication (+3dB) in 9 calibrated steps, response 5Hz to 100kHz (-3dB); input impedance 75k; calibration for 4, 8 and 16 ohm loads. *Preamp Mode:* sensitivity 15mV rms for +3dB indication; response 5Hz to 50k, input impedance 250k. *Sweep Mode:* display modes: left, right or dual trace; sensitivity: 1.6mV rms/cm (4.5mV p-p/cm); response: 5Hz to 50kHz (-3dB); input impedance 250k; sweep frequency: 20-20kHz in 3 decade ranges; sweep expansion 0.25X to 5X. Sweep triggers only when signal present, selectable trigger channel in dual trace mode. *Level Mode Times:* Normal: 250usec rise and 500ms decay; peak: 500usec rise and 25sec decay; reset: 250usec rise and 100 sec decay. *Low Pass Filter:* 16kHz LF filter for stereo and sweep modes; 19kHz and 38kHz rejected by 30dB. *CRT:* 3" round tube calibrated 5X6 cm. *Reticle Lights:* multipath = blue, stereo = red, level = amber, sweep = green. *Power Requirements:* 120 Volts at 50 watts.



MPI 4 - Sold from July 1973 - May 1977. S/N: AF1001~AF2793 (1,792 units)

Size: 5-7/16"H, 16"W and 13"D. Weight: 21 lb. **\$599.00**