

MCP 1

MOVING COIL PREAMPLIFIER

McIntosh
The Compendium



CONTROLS & CONNECTORS: LEFT INPUT: 90Ω, 40Ω, 20Ω, 10Ω. LED power indicator. LEFT OUTPUT. ⚡ RIGHT INPUT: 90Ω, 40Ω, 20Ω, 10Ω. ground binding post. RIGHT OUTPUT.



BACK PANEL: Power cord.

SPECIFICATIONS: **Input Impedances:** 10, 20, 40 and 90 ohms. **Gain:** 10 ohm = 30dB; 20 Ohm = 26dB; 40 ohm = 20dB; 90 ohm = 13dB. **Frequency Response:** 20-70kHz (0 -0.5dB). **Distortion:** 0.01%. **Signal to Noise Ratio:** -83dBA (re: 500uv input at 1k at 10 ohm input with RIAA equalization). **Phase Shift:** non-inverting. **Separation:** 90dB. **Power Requirements:** 120 Volts at 2 watts.

MCP 1

MOVING COIL PREAMPLIFIER

McIntosh
The Compendium



MCP 1 - Sold from September 1983 - June 1987. S/N: DJ1001~DJ1364 (363 UNITS)
Size: 3-3/16"H, 7"W and 5"D, **Weight:** 3 lb. **\$649.00**