

# MC 205

## FIVE CHANNEL POWER AMPLIFIER

CONFIGURABLE TO 3 + 2 CHANNELS

# McIntosh

The Compendium



**FRONT PANEL:** Glass with LED/fiber-optic illuminated green/gold nomenclature. 3 POWER GUARD lights: channel 1, 3 and 5. ⚡ Three illuminated POWER OUTPUT meters (linear WATTS or DECIBELS): channel 1, 3, and 5. ⚡ 2 POWER GUARD lights: channel 2 and 4. ⚡ Remote ON indicator light. ⚡ METER LIGHT switch: ON or OFF. POWER switch: ON or OFF STANDBY.



**BACK PANEL:** Speaker OUTPUTS connectors: 5 - Right Front, 2 - Right Back and 4 - Left Back. ↗ 1 - Left Front, 3 - center. ⚡ Power cord receptacle. FUSE. IMPEDANCE switch: 4, or 8 Ω. POWER CONTROL jacks: IN and OUT. INPUTS: channel 4 - Left Back balanced, channels 2 - right Back and 4 - Left Back unbalanced, channel 2 - Right Back balanced. Channel 5 - Right Front unbalanced, channels 5 - Right Front and 3 - center balanced, channels 1 - Left Front and 3 - center unbalanced, channel 1 - Left Front balanced.

# MC 205

## FIVE CHANNEL POWER AMPLIFIER

CONFIGURABLE TO 3 + 2 CHANNELS

# McIntosh

## The Compendium

**SPECIFICATIONS:** Five channels. **200w/ch** into 4 or 8 ohms. **Response:** 20-20kHz (+0 -0.25dB). **Distortion:** 0.005%. Noise and hum -112dBA. **Output Impedance:** 4 or 8 ohms. **Damping Factor:** >70 at 4 ohms or 140 at 8 ohms. **Input Impedance:** 10k unbalanced and 20k balanced. **Input Sensitivity:** 1v w/4ohm, 1.4v w/8ohm, balanced, and 2v w/4ohm, 2.8v w/8ohm, unbalanced. **Dynamic Headroom:** 1.7 dB. *Dynamic Power Manager. Sentry Monitor. Power Guard. Direct Coupled.* **Power Requirements:** 120V at 10 Amps.



**MC 205** - Sold from March 2007 - 2021. S/N: XT1001~XT???? and ACY1001~ACY????

**Size:** 9-7/16"H, 17-1/2"W and 21"D. **Weight:** 81 lb. **\$6,000.00**