

MC 2102

STEREO POWER AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. **METER** switch: LIGHTS OFF, WATTS or HOLD. Illuminated left and right **POWER OUTPUT** meters (linear WATTS, DECIBELS and BIAS SET). Remote ON indicator light. **POWER** switch: OFF, REMOTE or ON. Tubes can be seen through the clear rectangle above the meters.



BACK PANEL: Polished stainless steel chassis. Power cord receptacle. FUSE. RIGHT channel **OUTPUT** binding posts for 2 Ω , 4 Ω or 8 Ω speakers. LEFT channel **OUTPUT** binding posts for 2 Ω , 4 Ω or 8 Ω speakers. **POWER CONTROL** jacks: IN and OUT. **INPUT** switch: BALANCED or UNBALANCED. **MODE** switch: STEREO, PARALLEL or BRIDGED MONO. RIGHT audio **INPUTS**: UNBALANCED and BALANCED. LEFT audio **INPUTS**: BALANCED and UNBALANCED.

SPECIFICATIONS: 100w/ch into 2, 4 or 8 ohms. **Response:** 20-20kHz (+0 -0.25dB). **Distortion:** 0.5%. **Noise and Hum:** -100dBA. **Damping Factor:** greater than 18. **Input Impedance:** 20k unbalanced, 40k balanced. **Input Sensitivity:** 2.5V for balanced or 5.0V for unbalanced. Unity coupled. Sentry Monitor. Power requirements 120V at 5 Amps.

TUBES: 8-KT88/6550 output, 4-12AX7A, 2-12AT7. Solid state rectifier bridges.

MC 2102

STEREO POWER AMPLIFIER

McIntosh
The Compendium



MC 2102 - Sold from 2001 - 2013. S/N: TB1001~TB????

Size: 10-1/8"H, 17-3/4"W and 16"D. **Weight:** 88 lb. **\$6,100.00**