

MC 2301

MONAURAL TUBE POWER AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with LED/fiber-optic illuminated green/gold nomenclature. Illuminated **POWER OUTPUT** meter (linear **WATTS** or **DECIBELS**). ⚡ **METER** switch: **LIGHTS OFF, WATTS** or **HOLD**. Standby power on and sentry monitor indicator. **POWER** switch: **OFF, REMOTE** or **ON**. Handles. Tubes can be seen through the clear windows next to the meter.



BACK PANEL: Power cord receptacle. **CIRCUIT BREAKER**. **OUTPUT** binding posts for **2 Ω**, **4 Ω** or **8 Ω** speaker. **POWER CONTROL** jacks: **IN** and **OUT**. **UNBALANCED** audio **INPUT**. Input **MODE** switch: **UNBALANCED** or **BALANCED**. **BALANCED** audio **INPUT/OUTPUT**. Polished stainless steel chassis.

MC 2301

MONAURAL TUBE POWER AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: 300w into 2, 4 or 8 ohms. **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.5%. **Signal to Noise Ratio:** -117dBA. **Output Impedance:** 2, 4, or 8 ohms. **Damping Factor:** greater than 15. **Input Impedance:** 47K ohms. **Input Sensitivity:** 3.4v balanced and 1.7v unbalanced. Sentry Monitor. Quad Balanced™. *Autoformer*. Power requirements 120V at 5.5 Amps.



MC 2301 - Sold from 2008 - Current. S/N: YZ1001~YZ????

Size: 12-15/16"H, 17-3/4"W and 23"D. **Weight:** 116 lbs. **\$11,000.00**