

# MC 2600

## STEREO POWER AMPLIFIER

McIntosh  
The Compendium



**FRONT PANEL:** Black anodized aluminum panel. Illuminated LEFT and RIGHT POWER OUTPUT meters (linear WATTS or DECIBELS). ⚡ Left and right POWER GUARD lights. ⚡ LEFT GAIN control. METER switch: WATTS or HOLD. SPEAKER switch: OFF or ON. RIGHT/MONO GAIN control. HEADPHONES jack. POWER switch: ON or OFF. Handles.



**BACK PANEL:** Dual cooling fans. ⚡ Power cord receptacle. LEFT and RIGHT speaker OUTPUT barrier strips. UNBALANCED audio INPUTS: LEFT and RIGHT/MONO. BALANCED audio INPUTS: LEFT and RIGHT/MONO. MODE switch: STEREO, MONO BRIDGE or MONO PARALLEL. INPUT SENSITIVITY switch: 1.4V or 2.5V.

**SPECIFICATIONS:** 600w/ch. (1200w mono). **Response:** 20-20kHz (+0 -0.25dB). **Distortion:** 0.005%. **Noise and Hum:** -105dBA. **Output Impedance:** 2, 4, and 8 ohms stereo. (1, 2, 4, 8 and 16 ohms in mono). **Damping Factor:** 40 or greater. **Input Impedance:** 20k unbalanced, 40k unbalanced. **Input Sensitivity:** 1.4v or 2.5v. Sentry Monitor. Power Guard. Autoformers.

# MC 2600

## STEREO POWER AMPLIFIER

McIntosh  
The Compendium



**MC 2600** - Sold from 1990 - 1995. S/N: FS1001~FS????

**Size:** 19" rack mounting. 10-1/2"H and 18"D. **Weight:** 130 lb. **\$6,000.00**