

MC275 50TH Anniversary

STEREO POWER AMPLIFIER

McIntosh
The Compendium



CONTROLS & CONNECTORS: Polished stainless steel with super mirror gold finish/black chassis. LEFT speaker OUTPUT binding posts: COM, 4 Ω , 8 Ω , 16 Ω . RIGHT speaker OUTPUT binding posts: COM, 4 Ω , 8 Ω , 16 Ω . Standby Power On indicator. ⚡ POWER CONTROL jacks: IN and OUT. MODE switch: STEREO or MONO. INPUT switch: BALANCED or UNBALANCED. Left and Right/MONO audio XLR BALANCED INPUTS jacks. Left and Right/MONO audio UNBALANCED INPUTS jacks. POWER switch OFF/REMOTE or ON.



MC275 50TH Anniversary

STEREO POWER AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: 75w/ch stereo into 4, 8 or 16 ohms, 150w mono into 2, 4, or 8 ohms. **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.5%. **Signal To Noise Ratio:** -105dB (A weighted). **Output Impedance:** 4, 8, 16 ohms. (2, 4, and 8 ohms in Mono Mode). **Damping Factor:** greater than 22. **Input Impedance:** 47k unbalanced, 20k balanced. **Input Sensitivity:** 1.7V unbalanced, 3.4V balanced. *Unity Coupled.* **Power Requirements:** 120V at 3.6 Amps.

TUBES: 4-KT88/6550 output, 3-12AX7A, 4-12AT7. Solid state rectifier bridge.



MC275 50TH Anniversary features: 1. PCB wiring. 2. Stainless steel chassis with gold finish. 3. New design and 490 v power supply. 4. Sentry Monitor sequential testing/lighted bases for small tubes.

MC275 50TH Anniversary "Spotting features": 1. Gold McIntosh 275 50th Anniversary badges. 2. Large 5-way speaker binding posts on angled front panel. 3. All other connectors and controls are on the vertical front panel. 3. Unbalanced inputs on the right of the vertical front. 4. Power cord and fuse are on the rear panel. 5. Gold finish. 6. Output tubes are recessed. 7. Small tube light-up feature. 8. Power Control In/Out. 9. Power-on indicator.

MC275 50TH Anniversary - Sold 2012 - 2016 S/N: ABH1001~ABH???? ??? UNITS

Size: 8-1/4"H, 12"W and 16-1/2"D. **Weight:** 67 lb. **\$6,500.00**