

MC275 [MK IV]

STEREO POWER AMPLIFIER

McIntosh
The Compendium



CONTROLS & CONNECTORS: Polished stainless steel/black chassis. LEFT and RIGHT speaker OUTPUT barrier strips for 4, 8 and 16 OHMS. Left and Right (MONO) audio XLR BALANCED INPUTS jacks. Left and Right (MONO) UNBALANCED LEVEL controls: 2.5V to 1.0V. ⚡ POWER switch OFF or ON. Left and Right (MONO) audio UNBALANCED INPUTS. MODE switch: MONO or STEREO. INPUTS switch: BALANCED or UNBALANCED.



SPECIFICATIONS: 75w/ch stereo into 4, 8 or 16 ohms, 150w mono into 2, 4, or 8 ohms. **Response:** 20-20kHz (+0 -0.2dB). **Distortion:** 0.5%. **Noise & Hum:** -100dB (A weighted). **Output Impedance:** 4, 8, 16 ohms. (2, 4, and 8 ohms in mono), 25V line. **Damping Factor:** greater than 14. **Input Impedance:** 100k unbalanced, 180k balanced. **Input Sensitivity:** 1.2V unbalanced, 2.5V balanced. *Unity Coupled.* **Power Requirements:** 120V at 6.3 Amps.

TUBES: 4-KT88/6550 output, 3-12AX7A, 4-12AT7. Solid state rectifier bridge.

MC275 [MK IV]

STEREO POWER AMPLIFIER

McIntosh
The Compendium



MC275 [MK IV] features: **1.** PCB wiring. **2.** Stainless steel chassis. **3.** 450 v power supply.

MC275 [MK IV] "Spotting features": **1.** Power on-off switch. **2.** Gain controls. **3.** Unbalanced inputs right-center on the vertical front. **4.** Power cord and fuse are on the rear panel.

MC275 [MK IV] - Sold from March 2004 - December 2006. S/N: VN1001~VN????

Size: 8-1/4"H, 12"W and 16-1/2"D. **Weight:** 67 lb. **\$3,000.00**