

MC 2KW

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium



OUTPUT MODULE FRONT PANEL: LED/fiber-optic illuminated green/gold nomenclature. Illuminated POWER OUTPUT meter (linear WATTS or DECIBELS). POWER GUARD LED. ⚡ METER mode switch: LIGHTS OFF, WATTS or HOLD. POWER switch: OFF, REMOTE or ON. Handles.



OUTPUT MODULE BACK PANEL: Speaker OUTPUTS connectors: 2 Ω - A, B and C. ⚡ Speaker OUTPUTS connectors: 4 Ω - A, B and C. ⚡ Speaker OUTPUTS connectors: 8 Ω - A, B and C. ⚡ MAIN FUSE. ⚡ Power cord receptacle. TO POWER MODULE (A) 16 pin connector 1 and 2. POWER CONTROL jacks: IN and OUT. BALANCED audio OUTPUT. 2 BALANCED audio INPUTS. INPUT MODE switch: BALANCED or UNBALANCED. UNBALANCED Input and OUTPUT. TO POWER MODULE (B) 16 pin connector 1 and 2. Polished stainless steel chassis.

MC 2KW

MONAURAL POWER AMPLIFIER

McIntosh
The Compendium



POWER MODULES (2) FRONT PANEL: LED/fiber-optic illuminated green/blue/white **McIntosh** logo and nomenclature. Handles.



POWER MODULES (2) BACK PANEL: Polished stainless steel chassis. Power cord receptacle. CIRCUIT BREAKER. TO OUTPUT MODULE (1) 16 pin connector. TO OUTPUT MODULE (2) 16 pin connector.

MC 2KW

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: 2000w into 2, 4 or 8 ohms. **Response:** 20-20kHz (+0 -0.25dB). **Response:** 10-100kHz (+0 -3 dB). **Distortion:** 0.005%. **Noise and Hum:** -123dBA unbalanced, -127dBA balanced. **Output Impedance:** 2, 4 or 8 ohms. **Damping Factor:** >40. **Input Impedance:** 10k balanced. **Input Sensitivity:** 2.5v unbalanced, and 5v balanced. **Dynamic Headroom:** 2 dB. Sentry Monitor. **Autoformers.** Quad Balanced™. Power Guard. **Power Requirements:** 120V at 12 Amps.



MC 2KW - Sold from October 2005 - Current. S/N: XJ-C001~XJ-C???

Output Module Size: 12-5/16"H, 17-3/4"W and 26-5/8"D. **Weight:** 121 lb.

Power Module (2 each) Size: 12-5/16"H, 17-3/4"W and 26-5/8"D. **Weight:** 158 lb.

\$30,000.00