

MC 303

THREE CHANNEL POWER AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with LED/fiber-optic illuminated green/gold nomenclature. Channel 1, 2 and 3 POWER GUARD indicators. ⚡ Illuminated channel 1, 2 and 3 POWER OUTPUT meters (linear WATTS or DECIBELS). ⚡ METER LIGHTS switch: OFF, AUTO. Standby power on indicator. POWER switch: OFF, REMOTE or ON.



BACK PANEL: Polished stainless steel chassis. [BALANCED audio INPUT 3. ⚡ UNBALANCED audio INPUT 3. ⚡ POWER CONTROL jacks: IN and OUT.] ↗ [BALANCED audio INPUT 2. ⚡ UNBALANCED audio INPUT 2. ⚡ BALANCED audio INPUT 1. UNBALANCED audio INPUT 1.] ⚡ OUTPUT 3 binding posts for 2 Ω, 4 Ω or 8 Ω speakers. Power cord receptacle. OUTPUT 2 binding posts for 2 Ω, 4 Ω or 8 Ω speakers. FUSE. OUTPUT 1 binding posts for 2 Ω, 4 Ω or 8 Ω speakers.

SPECIFICATIONS: 300w/ch into 2, 4 or 8 ohms. **Response:** 20-20kHz (+0 -0.25dB). **Distortion:** 0.005%. **Signal to Noise Ratio:** -112dBa. **Output Impedance:** 2, 4, or 8 ohms. **Damping Factor:** greater than 40. **Input impedance:** 10K. **Input Sensitivity:** 3.4v balanced and 1.7v unbalanced. **Dynamic Headroom:** 1.8 dB. Sentry Monitor. Power Guard. **Autoformers.** Power requirements 120V at 10 Amps.

MC 303

THREE CHANNEL POWER AMPLIFIER

McIntosh
The Compendium



MC 303 - Sold from 2008 - Current. S/N: ZH1001~ZH????

Size: 12-3/8"H, 17-3/4"W and 22"D. **Weight:** 155 lbs.

\$10,000.00