

# MC 3500

## MONAURAL TUBE POWER AMPLIFIER

# McIntosh

## The Compendium



**FRONT PANEL:** Black and anodized aluminum panel. Illuminated **METER:** monitors **OUTPUT VOLTAGE**, **DECIBELS** or **CATHODE CURRENT** for each output tube. ⚡ **INPUT** connectors: **RCA** and **BNC**. **GAIN CONTROL**. **METER RANGE SWITCH:** **OFF**, **VOLTS**, **dB**, **dB-10** or **V1-V8**. **POWER CIRCUIT BREAKER:** **ON** or **OFF**. **OUTPUT RANGE SWITCH:** **1**, **4**, **8**, **16**, **50**, and **64 OHMS** with corresponding voltages **17.3**, **35.8**, **53.0**, **75.0**, **132** and **150V**. Dual banana **OUTPUT** connectors. Heavy duty handles.



**BACK PANEL:** Cooling fan. ⚡ **Power cord** receptacle. **FUSE**. **LINE VOLTAGE SWITCH:** **117** or **125V**. **Speaker OUTPUT 1** and **2** barrier strip. **TRANSFORMER INPUT**. **Audio INPUT 1** and **2** terminals. **SUBSONIC FILTER** switch: **OUT** or **IN**.

**TUBES:** 8-**6LQ6/6JE6B** output, 2-**12AX7/ECC83**, 2-**6DJ8/ECC88**, **6CG7/6FQ7** and **6BL7GTA**. Solid state rectifier bridge. Direct coupled.

# MC 3500

## MONAURAL TUBE POWER AMPLIFIER

# McIntosh

## The Compendium

**SPECIFICATIONS:** 350w. **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.15%.  
**Noise & Hum:** - 95dB. **Output Impedance:** 1, 4, 8, 16, 50 and 64 ohms. All impedances can be isolated from ground. **Internal Impedance:** less than 5% of rated impedance. **Input Impedance:** 200k. **Input Sensitivity:** 1.1V.



**MC 3500** - Sold from February 1968 - June 1971. S/N: 10N01~11N95 (193 UNITS)

**Size:** 19" rack mounting. 10-1/2"H, and 17"D behind panel. **Weight:** 125 lb. **\$1,099.00**