

MC 601

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with LED green nomenclature. Illuminated POWER OUTPUT meter (linear WATTS or DECIBELS). Power guard LED. Standby power On indicator. ⚡ METER switch: LIGHTS OFF, WATTS or HOLD. POWER switch: OFF, REMOTE or ON. Handles.



BACK PANEL: POWER CONTROL jacks: IN, OUT 1 and 2. BALANCED input. UNBALANCED: input/output. BALANCED output. INPUT MODE switch: UNBALANCED or BALANCED. ⚡ Polished stainless steel chassis. Gold plated OUTPUT terminals for 8 Ω , 4 Ω , or 2 Ω speakers. FUSE. Power cord receptacle.

SPECIFICATIONS: 600w into 2, 4 or 8 ohms. **Response:** 20-20kHz. **Distortion:** 0.005%. **Signal to Noise Ratio:** -96dBA balanced, -94dBA unbalanced. **Output Impedance:** 2, 4, or 8 ohms. **Wide Band Damping Factor:** greater than 40. **Input Impedance:** 22K balanced and unbalanced. **Input Sensitivity:** 4.8v balanced and 2.4v unbalanced. **Dynamic Headroom:** 1.8 dB. Sentry Monitor. Power Guard. *Autoformers*, Quad Balanced™. Power requirements 120V at 6.6 Amps.

MC 601

MONAURAL POWER AMPLIFIER

McIntosh
The Compendium



MC 601 - Sold from 2011 - 2020. S/N: ACH1001~ACH???? and AAY1001~AAY????
Size: 9-7/16"H, 29-1/2"W and 22"D. **Weight:** 93 lbs. **\$6,000.00**