

MC 602

STEREO POWER AMPLIFIER

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated green/gold nomenclature. Illuminated left and right POWER OUTPUT meters (linear WATTS or DECIBELS). Left and right POWER GUARD lights. ⚡ METER switch: LIGHTS OFF, WATTS or HOLD. Remote ON indicator light. POWER switch: OFF, REMOTE or ON.



BACK PANEL: POWER CONTROL jacks: OUT and IN. LEFT and RIGHT BALANCED INPUTS. LEFT and RIGHT UNBALANCED INPUTS. INPUT MODE switch: BALANCED or UNBALANCED. ⚡ Polished stainless steel chassis. CIRCUIT BREAKER. Gold plated RIGHT channel OUTPUT terminals for 2, 4, or 8 Ω speakers. Gold plated LEFT channel OUTPUT terminals for 2, 4, or 8 Ω speakers. Power cord receptacle.

MC 602

STEREO POWER AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: 600w/ch into 2, 4 or 8 ohms. **Response:** 20-20kHz (+0 -0.25dB). **Distortion:** 0.005%. **Signal to Noise Ratio:** -124dBA balanced, -120dBA unbalanced. **Output Impedance:** 2, 4, or 8 ohms. **Damping Factor:** 100 at 8 ohms. **Input Impedance:** 10K balanced and 20K unbalanced. **Input Sensitivity:** 4.9v balanced and 2.45v unbalanced. **Dynamic Headroom:** 2.1 dB. Sentry Monitor. Power Guard. **Autoformers.** Power requirements 120V at 15 Amps.



MC 602 - Sold from 2003 - 2007. S/N: RX1001~RX????

Size: 11"H, 17-3/4"W and 19.63"D. **Weight:** 155 lbs.

\$8,100.00