

# MC 75

## MONAURAL POWER AMPLIFIER

# McIntosh

## The Compendium



**CONTROLS & CONNECTORS:** Chrome/black chassis. Octal socket for 70V/600 OHM OUTPUTS. SPEAKER OUTPUT barrier strip for 4, 8 and 16 OHMS. GAIN control with 2.0 V SETTING FOR MCINTOSH PREAMP. ⚡ Power cord. FUSE. AC outlet. LINE VOLTAGE switch: 117 or 125V. 0.5 VOLT audio INPUT.



**SPECIFICATIONS:** 75w. **Response:** 16-40kHz (+0 -0.1dB). **Distortion:** 0.5%. **Noise & Hum:** -90dB. **Output Impedance:** 4, 8, 16, 67, 150 and 600 ohms. 600 ohm balanced to ground. 4, 8 and 16 ohms isolated from ground. **Output Voltages:** 25, 70.7, 115 and 230V. 230V winding center tapped. **Internal Impedance:** less than 10% of rated impedance. **Input Impedance:** 250k. **Input Sensitivity:** 0.5V (2.0V with gain control switched at maximum). *Unity Coupled.*

**TUBES:** 2-KT88/6550 output, 12AX7, 12AU7, 12BH7, 12AZ7 or 12AT7. Solid state rectifier.

# MC 75

**MONAURAL POWER AMPLIFIER**

**McIntosh**  
The Compendium



**MC 75** - Sold from June 1961 - May 1970. S/N: 100B1~632B0 (9,981 UNITS)

**Size:** 8-1/4"H, 8-1/4"W and 16-3/4"D. **Weight:** 44 lb. **\$229.00**