

# CR 7

## REMOTE CONTROL SYSTEM

McIntosh  
The Compendium



**FRONT PANEL:** Black anodized aluminum panel. IR SENSOR. ⚡ Touch buttons (with indicators): POWER, TUNER, CD, PREAMP. Touch buttons: MUTE, ▼ VOLUME, (SYSTEM OFF), VOLUME ▲.



**BACK PANEL:** OUTPUT: L & R. Input: PREAMP: L & R. CD: L & R. TUNER: L & R. ⚡ Power cord. AC outlets: 1 UNSWITCHED, 1 POWER AMP, 1 PREAMP. SYSTEM SENSOR coax connector. DIN CD CONTROL connector. 15 pin TUNER CONTROL connector. 25 pin TO AREA CONTROLLER connector.

**SPECIFICATIONS:** **Response:** 20-20k (+0 -0.5). **Output:** 2.5V (5V max). **Sensitivity:** 0.775V (5V max) all inputs. **Distortion:** 0.007%. **Signal to Noise Ratio:** -84dBa IHF. **Input Impedance:** 100k. **Power Requirements:** 120 Volts at 8 watts. Has **HR07** hand remote.

**CR 7** - Sold from September 1986 - 1991. S/N: EL1001~EL????

**Size:** 3-1/16"H, 8-3/16"W and 9-1/2"D. **Weight:** 6 lb. **\$849.00**