

CR 8

REMOTE AREA CONTROLLER



FRONT PANEL: Black anodized aluminum panel. POWER indicator light.



BACK PANEL: Left and right OUTPUT. ⚡ Power cord. AC outlets: 1 UNSWITCHED, 1 POWER AMP. Coax AREA SENSOR connector. 25 pin TO NEXT AREA CONTROLLER output connector. 25 pin AREA CONTROLLER INPUT connector.

SPECIFICATIONS: **Frequency Response:** 20-20k (+0 -0.5). **Output:** 2.5V (5V max). Sensitivity: 0.775V (5V max) all inputs. **Distortion:** 0.007%. **Signal to Noise Ratio:** -84dBa IHF. **Input Impedance:** 100k. **Power Requirements:** 120 Volts at 8 watts. Has **HR7** hand remote.



CR 8 - Sold from September 1986 - 1991. S/N: EM1001~EM????

Size: 3-1/16"H, 8-3/16"W and 9-1/2"D. **Weight:** 6 lb. **\$678.00**