

MR 7082

AM - FM STEREO TUNER

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature and anodized black aluminum panel. Indicators for: FM, AM, SEARCH, MONO, MONOPLUS, STEREO. Digital frequency readout. FM MPX light. TUNING lights: ▶, • (lock) and ◀. LED indicators for SIGNAL strength. ⚡ Push Buttons: FM, AM, SEARCH, MANUAL, POWER, MONO, MONOPLUS, STEREO. Preset stations with indicator lights: 1, 2, 3 and 4, SCAN ▲. Preset stations with indicator lights: 5, 6, 7, SCAN ▼, ENTER. Tuning control with manual tuning indicator light. PANLOC buttons.



EARLY



LATE

BACK PANEL: Power cord. 75 Ω FM ANTenna coax input. Push terminals for GND and external AM ANTenna. 15 pin REMOTE CONTROL receptacle. Left & Right fixed AUDIO OUTPUT. (late units had FIXED and VARIABLE outputs and an OUTPUT LEVEL adjustment). Panloc mounting.

FM SECTION: **Sensitivity:** 13dB μ V or 1.22uV across 75 ohms. **Stereo 50dB Quieting Sensitivity:** 37dB μ V or 20uV across 75 ohms. **Response:** 20-15kHz (+0 -1dB). **Distortion:** 0.08% in stereo. **Capture Ratio:** 1.5dB. **Image Rejection:** 90dB. **S/N:** 75dB stereo. **Alternate Channel Selectivity:** 55dB. **Spurious Rejection:** 100dB. **AM Suppression:** 60dB.

AM SECTION: **Sensitivity:** 35uV. **Response:** 20-4.5kHz (+0 -6dB). **Distortion:** 0.3%. **Adjacent Channel Selectivity:** 40dB. **S/N:** 65dB. **Image Rejection:** 60dB.

Power Requirements: 120V at 10 Watts.

CABINET: L 52

PANLOC BRACKETS: Right - 046-574 / Left - 046-575

MR 7082

AM - FM STEREO TUNER

McIntosh
The Compendium



MR 7082 - Sold from May 1986 - 1990. S/N: EE1001~EE????

Size: 5-7/16"H, 16-1/8"W and 13"D behind panel. **Weight:** 15 lb. **\$1,579.00**