

MR 77

FM STEREO TUNER

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. Illuminated tuning dial. STEREO MPX indicator. Electron ray tube MULTIPATH indicator. Illuminated SIGNAL STRENGTH meter. Illuminated TUNING meter. Tuning control. ⚡ MODE SELECTOR switch: MONO, AUTO or STEREO. STEREO FILTER switch: OUT, 1 or 2. MUTING switch: OUT, DISTANT or LOCAL. VOLUME with on-OFF switch. PANLOC buttons.



BACK PANEL: TP1 and TP2 scope outputs. Switched AC outlet. FUSE. Power cord. Push terminals for FM ANTENNA: GND, 300 Ω FM ANTENNA. 75 Ω FM ANTENNA coax input. LEFT & RIGHT AUDIO OUTPUTS: 2.5V FIXED OUTPUT and FRONT PANEL CONTROLLED. Panloc mounting.



TOP PANEL: DIAL SCALE INTENSITY: DIM or BRIGHT.

FM SECTION: **Sensitivity:** 2uV for 35dB of quieting. **Response:** 20-15kHz (+1 – 1dB). **Distortion:** 0.2% in stereo. **Capture Ratio:** 2.5dB. **Image Rejection:** 100dB. **S/N:** 75dB. **Separation:** 40dB@1kHz. **Spurious Rejection:** 100dB. **Alternate Channel Selectivity:** 90dB. **Adjacent Channel Selectivity:** 47dB. **SCA Rejection:** 50dB. **Power Requirements:** 120V at 35 Watts.



CABINET: L 12 Also fits L 11, L 52, and L 62

MR 77

FM STEREO TUNER

McIntosh
The Compendium

PANLOC BRACKETS: Right - **043-592** / Left - **043-593**



MR 77 - Sold from June 1970 - 1977. S/N: 10Y01~60Y18 (5,016 UNITS)

Size: 5-7/16"H, 16"W and 13"D behind panel. **Weight:** 27 lb. **\$699.00**