

MR 78

FM STEREO TUNER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. **FUNCTION** indicator: STEREO, FILTER or MUTING. **SELECTIVITY** indicator: -7 dB, -22 dB or -55 dB. Illuminated tuning dial. Illuminated **SIGNAL STRENGTH** meter. Illuminated tuning meter. Tuning control. ⚡ **SELECTIVITY** switch: NORMAL, NARROW or SUPER NARROW. **METER** switch: SIGNAL STRENGTH or MULTIPATH. **FILTER** switch: OUT, 1 or 2. **MUTING** switch: OUT, DISTANT or LOCAL. **MODE** switch: STEREO ONLY, MONO or STEREO AUTO. **VOLUME** with on-OFF switch. PANLOC buttons.



BACK PANEL: TP1 and TP2 scope outputs. FUSE. Switched AC outlet. Power cord. Push terminals for GND, 300 Ω ANTENNA. 75 Ω FM ANTENNA coax input. LEFT & RIGHT AUDIO OUTPUTS : 2.5V FIXED OUTPUT and FRONT PANEL CONTROLLED. Panloc mounting.



TOP PANEL: ANTENNA MATCHING switch: HIGH GAIN ANT. or LOW GAIN ANT. DIAL SCALE INTENSITY switch: DIM or BRIGHT.

FM SECTION: **Sensitivity:** 2uV for 35dB of quieting. **Response:** 20-15kHz (+1 -1dB). **Distortion:** 0.2% in stereo. **Capture Ratio:** 2.5dB. **Image Rejection:** 100dB. **S/N:** 75dB. **Separation:** 40dB@1kHz. **Spurious Rejection:** 100dB. **SCA Rejection:** 50dB. **Power Requirements:** 120V at 35 Watts.

CABINET: L 12 Also fits L 11, L 52, and L 62



MR 78

FM STEREO TUNER

McIntosh
The Compendium

PANLOC BRACKETS: Right – **043-592** / Left – **043-593**



MR 78 - Sold from October 1972 - 1984. S/N: AD1001~AD9999 & CG1001~CG2804 (10,801 UNITS)

Size: 5-7/16"H, 16"W and 13"D behind panel. **Weight:** 27 lb. **\$1,699.00**