

A 116

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium



CONTROLS & CONNECTORS: Gray hammer tone finish. Power cord. Octal OUTPUT socket powers **McIntosh C 8, C 4, C 104, or C 108** preamps. HUM ADJUSTMENT. .5V INPUT. .5V INPUT ADJ. Octal PRE-AMP INPUT socket. ⚡ FUSE. Speaker OUTPUT connector strip for 16, 8 and 4 ohms as well as .5V INPUT.



SPECIFICATIONS: 30w. **Response:** 20-30kHz (+0.1 -0.1dB). **Distortion:** 0.5%.

Noise & Hum: - 85dB. **Output Impedance:** 4, 8, 16, and 600 ohms. 600 ohm balanced to ground. 4, 8 and 16 ohms isolated from ground. **Damping Factor:** 12 for 4, 8 and 16 ohms. **Input Impedance:** 500k. **Input Sensitivity:** 0.5V.

TUBES: 2-6BG6 output, 12AX7, 12AU7, 12BH7, 5U4GA.

A 116

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium



A 116 - Sold from January 1953 - July 1954. S/N: 5,000-8,515 (3,515 UNITS)

Size: 8-1/4"H, 8"W and 12"D. **Weight:** 33 lb. **\$143.50**