

# MC 202

## STEREO POWER AMPLIFIER

# McIntosh

## The Compendium



**FRONT PANEL:** Glass with illuminated teal/gold nomenclature. Illuminated left and right POWER OUTPUT meters (LINEAR WATTS or DECIBELS). Left and right POWER GUARD lights. ⚡ METER switch: LIGHTS OFF, WATTS or HOLD. Remote ON indicator. POWER switch: OFF, REMOTE or ON.



**BACK PANEL:** FUSE. Power cord receptacle. UNBALANCED Left and Right/MONO INPUTS. BALANCED Right/MONO and Left INPUTS. MODE switch: STEREO or MONO BRIDGED. POWER CONTROL jacks: IN and OUT. ⚡ RIGHT speaker OUTPUT connectors for 2 Ω, 4 Ω and 8 Ω. LEFT speaker OUTPUT connectors for 2 Ω, 4 Ω and 8 Ω.

**SPECIFICATIONS:** 200w/ch into 2, 4 or 8 ohms. **Response:** 20-20kHz (+0 -0.25dB). **Distortion:** 0.005%. **Signal to Noise Ratio:** -115dBa. **Output Impedance:** 2, 4 or 8 ohms, mono bridged: 4, 8 or 16 ohms. **Damping Factor:** >40. **Input Sensitivity:** 1.7v unbalanced, 3.4v balanced. **Dynamic Headroom:** 1.9 dB. Sentry Monitor. **Autoformers.** Power Guard. **Power Requirements:** 120V at 5 Amps.



# MC 202

STEREO POWER AMPLIFIER

McIntosh  
The Compendium



**MC 202** - Sold from 2000 - 2003. S/N: RY1001~RY????

**Size:** 5-3/8"H, 17-1/2"W and 17-1/2"D. **Weight:** 65 lb. **\$3,300.00**