

MC 301

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with LED/fiber-optic illuminated green nomenclature. Illuminated POWER OUTPUT meter (linear WATTS or DECIBELS). POWER GUARD light. ⚡ Standby Power On Indicator. ⚡ METER LIGHT switch: ON or OFF. POWER switch: ON or OFF.



BACK PANEL: INPUT MODE switch: BALANCED or UNBALANCED. BALANCED INPUT. UNBALANCED In/out, BALANCED OUTPUT. POWER CONTROL jacks: IN and OUT. AUTO OFF Power Save switch: DISABLED or ENABLED. ⚡ FUSE. Power cord receptacle. Gold plated speaker OUTPUT terminals for 2, 4 and 8 ohms.

SPECIFICATIONS: 300w. **Frequency Response:** 20-20kHz (+0 -0.25dB), 10- 100kHz (+0 -3.0dB). **Distortion:** 0.005%. **Signal to Noise Ratio:** -95dBA, balanced; -93dBA, unbalanced. **Dynamic Headroom:** 2dB. **Output Impedance:** 2, 4 or 8 ohms. **Damping Factor:** 40 or greater. **Input Impedance:** 22k, balanced or unbalanced. **Input Sensitivity:** 3.4v, balanced; 1.7, unbalanced. **Voltage Gain:** 23dB, 2 ohms; 26dB, 4 ohms; 29dB, 8 ohms. Sentry Monitor. Power Guard. Quad Balanced™. Autoformer. **Power Requirements:** 120V at 3.7 Amps.

MC 301

MONAURAL POWER AMPLIFIER

McIntosh
The Compendium



MC 301 - Sold from 2014 - 2021. S/N: ADU1001~ADU????

Size: 6"H, 17-1/2"W and 21"D. **Weight:** 67 lb. **\$5,000.00**