

MC 611

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with LED green nomenclature. Illuminated **POWER OUTPUT** meter (linear **WATTS** or **DECIBELS**). Power guard LED. Standby power On indicator. ⚡ **METER** switch: **LIGHTS OFF**, **WATTS** or **HOLD**. **POWER** switch: **OFF**, **REMOTE** or **ON**. Handles.



BACK PANEL: **POWER CONTROL** jacks: **IN**, **OUT 1** and **2**. **BALANCED OUTPUT**. **UNBALANCED:** **INPUT/OUTPUT**. **BALANCED INPUT**. **AUTO OFF:** **ENABLED** or **DISABLED**. **INPUT MODE** switch: **UNBALANCED** or **BALANCED**. ⚡ Polished stainless steel chassis. **FUSE**. Gold plated **OUTPUT** terminals for **8 Ω**, **4 Ω**, or **2 Ω** speakers. ⚡ Power cord receptacle.

SPECIFICATIONS: **600w** into 2, 4 or 8 ohms. **Response:** 20-20kHz +0,-0.25dB; 20-100kHz +0,-3.0dB **Distortion:** 0.005%. **Signal to Noise Ratio:** -124dBA balanced, -120dBA unbalanced. **Output Impedance:** 2, 4, or 8 ohms. **Wide Band Damping Factor:** greater than 40. **Input Impedance:** 22K balanced and unbalanced. **Input Sensitivity:** 4.8v balanced and 2.4v unbalanced. **Dynamic Headroom:** 2.8 dB. Sentry Monitor. Power Guard. Autoformers. Quad Balanced™. Power requirements 120V at 6.6 Amps.

MC 611

MONAURAL POWER AMPLIFIER

McIntosh
The Compendium



MC 611 - Sold from February 2018 - Current. S/N: AGF1001~AGF????
Size: 9-7/16"H, 29-1/2"W and 22"D. **Weight:** 97.5 lbs. **\$7,500.00**